

SR-1002

INDOOR SMOKE DETECTOR



DESCRIPTION:

A good quality smoke detector used in a home or apartment is a guarantee of safety and protection in case of fire or smoke in rooms. The Lanberg SR-1002 is a laboratory-tested, high-performance sensor that complies with the latest standards. Simple operation, stable operation and high functionality are the main advantages of the device.

PRODUCT SPECIFICATION:

- Operating voltage: 9V DC
- Static operating current: >12mA
- Alarm Current: > 20mA
- Alarm loudness / effective range: >85db/3m
- Normal status indication: Red LED flashes every 43s.
- Alarm status: Constant sound / light signals
- Low battery voltage alarm: >7.35V - sound alarm every 43s.
- Test / HUSH mode: Red LED flashes every 10s
- Operating temperature: -10~+40
- Operating humidity: 95%RH (no condensation)

Accordance with EN 14604:2005/AC:2008 standard confirmed by notified body, in the European Union